## **LUMINOUS TUBE FOOTAGE CHART**

Ventex Model Number	Туре	Secondary Current	Neon Footage			Mercury Footage		
Tube Size in Millimeters			10mm	12mm	15mm	10mm	12mm	15mm
1,500V Secondary Voltage								
VT1510-12	Indoor	15mA*	3 ft	4 ft	5 ft	4 ft	5 ft	6 ft
3,000V Secondary Voltage								
VT3015S-12	Indoor	15mA*	8 ft	10 ft	11 ft	10 ft	12 ft	13 ft
4,000V Secondary Voltage								
VT4015-12	Indoor	15mA*	8 ft	10 ft	11 ft	10 ft	12 ft	13 ft
VT4015A-12F	Indoor	15mA*	8 ft	10 ft	11 ft	10 ft	12 ft	13 ft
VT4030-120	Indoor	30mA	8 ft	10 ft	15 ft	10 ft	12 ft	16 ft
VT4030CL-120/277	Outdoor	30mA	8 ft	10 ft	15 ft	10 ft	12 ft	16 ft
VT4060CL-120/240/277	Outdoor	60mA	8 ft	10 ft	15 ft	10 ft	12 ft	16 ft
5,500V Secondary Voltage								
VT5520-120F & VT5520-120F	Indoor	20mA	11 ft	13 ft	18 ft	13 ft	16 ft	21 ft
6,000V Secondary Voltage								
VT6030-120/240	Indoor	30mA	13 ft	16 ft	22 ft	16 ft	20 ft	26 ft
VT6030CL-120/240	Outdoor	30mA	13 ft	16 ft	22 ft	16 ft	20 ft	26 ft
VT6060CL-120	Outdoor	60mA	13 ft	16 ft	22 ft	16 ft	20 ft	26 ft
9,000V Secondary Voltage								
VT9030-120	Indoor	30mA	21 ft	26 ft	34 ft	24 ft	31 ft	40 ft
VT9030D-120	Indoor	30mA	21 ft	26 ft	34 ft	24 ft	31 ft	40 ft
VT9030CL-120/240/277	Outdoor	30mA	21 ft	26 ft	34 ft	25 ft	31 ft	40 ft
VT9060CL-120/277	Outdoor	60mA	21 ft	26 ft	34 ft	25 ft	31 ft	40 ft
12,000V Secondary Voltage								
VT12030-120/240	Indoor	30mA	28 ft	35 ft	45 ft	33 ft	42 ft	54 ft
VT12030D-120	Indoor	30mA	28 ft	35 ft	45 ft	33 ft	42 ft	54 ft
VT12030CL-120	Outdoor	30mA	28 ft	35 ft	45 ft	33 ft	42 ft	54 ft
Recommended Gas Pressure mm/Hg			13	11	9	13	11	9

## NOTES:

- · The above footage chart is intended to be a guideline. Actual driving distances may vary due to application.
- VT Series electronic supplies have overload shut-down protection. If activated, unit will flash (trip-off) to protect itself and must be turned off/on to reset protection.
- · Ventex electronic power supplies are fully self-adjusting from minimum to maximum voltage protection.
- Do not load with mA meter. Ventex electronic power supplies will self-regulate to maintain 30 to 60mA regardless of load.
- · Deduct driving distances by one foot and two feet for each pair of electrodes.
- Neon Power Supply loading must be de-rated by 10% for every 9°F (5°C) above maximum running ambient or below minimum running ambient.
- "Triple-Shot" automatically turns on up to 3 times in about 4 seconds.

 $\textbf{WARRANTY:} \ \ \text{For detailed warranty information, visit www.ventextech.com}.$